论文

电流非均匀分布对磁绝缘感应电压叠加器电子鞘层的影响

魏浩^{1,2*}, 孙凤举², 邱爱慈^{1,2}, 呼义翔²

1. 西安交通大学电力设备电气绝缘国家重点实验室, 西安 710049;

2. 西北核技术研究所强脉冲辐射环境模拟与效应国家重点实验室, 西安 710024

*联系人, E-mail: weihao@nint.ac.cn

收稿日期: 2017-09-19; 接受日期: 2017-11-08; 网络出版日期: 2017-12-28

国家自然科学基金(编号: 11505138, 51577156)资助项目

摘要 磁绝缘感应电压叠加器(MIVA)感应腔注入电流空间非均匀分布对次级磁绝缘电子鞘层和功率流传输产生影响. 本文基于磁绝缘稳态二维层流模型, 分析了电流非均匀分布对MIVA次级电子鞘层的影响规律. 电流非均匀分布对磁绝缘电子鞘层影响较大, 但对电荷质心和磁绝缘流阻抗影响较小. 对于给定磁绝缘参数(线电压 $V_0=4.1$ MV、最小阳极电流 $I_{amin}=132$ kA), 当阴极电流不均匀系数 δ_c 约35%时, 电子鞘层不均匀系数 ζ 约79.4%, 流阻抗减小了5.6%; 当 δ_c 增大至69.5%时, 电子鞘层偏心导致阴-阳间隙局部短路. 在磁绝缘最小阳极电流 I_{amin} 相同时, 线电压 V_0 越低, 电流非均匀分布的影响程度越显著. 当线电压 V_0 由4.2 MV降低至1.4 MV时, 引发间隙局部短路的阴极电流不均匀系数由69.5%降低至35%.

关键词 磁绝缘感应电压叠加器(MIVA), 电流非均匀分布, 非轴对称磁绝缘, 电子鞘层

PACS: 52.59.-f, 29.20.Ej, 41.75.Ht, 41.20.Cv, 84.70.+p

1 引言

超高功率脉冲技术是获得高温、高压、高能量密度和强辐射等极端物理实验条件的重要手段^[1-4], 是高能量密度物理^[5-9]、Z箍缩惯性约束聚变^[10-15]、先进辐射源^[16-19]等前沿科学研究的关键支撑技术. 磁绝缘感应电压叠加器(Magnetically Insulated Induction Voltage Adders, MIVA)可产生电压数十兆伏、电流数百千安的高功率电脉冲^[20-22], 在强脉冲辐射环境模拟和高能

脉冲X射线闪光照相等领域具有重要应用^[23-26], 成为近年来国内外研究热点. 美国Sandia国家实验室、英国原子能武器研究中心均在开展输出电压为14–16 MV, 电流为120–180 kA的大型MIVA装置研制和技术研究^[27,28].

MIVA由多个兆伏级感应腔串联组成. 前级脉冲源产生多路电压约1 MV电脉冲从感应腔侧壁径向注入, 基于电磁感应原理, 注入脉冲在次级中心内筒上感应叠加^[20-22]. MIVA次级通常采用磁绝缘传输线

引用格式: 魏浩, 孙凤举, 邱爱慈, 等. 电流非均匀分布对磁绝缘感应电压叠加器电子鞘层的影响. 中国科学: 物理学 力学 天文学, 2018, 48: 025203
Wei H, Sun F J, Qiu A C, et al. Effects of current asymmetry on the electron sheath of magnetically-insulated induction voltage adders (in Chinese). Sci Sin-Phys Mech Astron, 2018, 48: 025203, doi: 10.1360/SSPMA2017-00263

(Magnetically Insulated Transmission Lines, MITL)提高输出电压和功率密度^[20-22]. 当MIVA作为X射线闪光灯相驱动源时, 每级感应腔一般仅馈入单路脉冲, 这种馈入方式导致注入电流空间非均匀分布^[29-31], 从而对感应腔电气参数、功率传输和MIVA性能产生影响^[32-35]. 特别地, 电流非均匀分布会引起次级MITL电子非均匀发射、电子鞘层偏心等非轴对称磁绝缘特性, 从而对功率流传输产生影响^[29,30,32-34].

感应腔注入电流非均匀分布及其影响是单路馈入MIVA的研究重点. 美国Sandia国家实验室Oliver等人^[30]提出采用磁绝缘经典Creedon理论描述MIVA次级非轴对称磁绝缘的稳定状态, 并给出了磁绝缘空间电子满足的数学物理方程. Bruner等人^[32,33]采用三维全尺寸粒子模拟(Particle In Cell, PIC)方法, 给出了电流非均匀分布对MIVA电子鞘层时空演化的影响. 但上述研究未能给出电流非均匀分布程度与磁绝缘特性之间的定量关系. 本文基于非轴对称磁绝缘二维Creedon模型^[36,37], 数值分析了电流非均匀分布对磁绝缘特性(电子鞘层、流阻抗)的影响规律.

需要指出的是, 电流非均匀分布对MIVA次级磁绝缘特性的影响程度与MITL运行参数密切相关. 与超磁绝缘状态(阳极电流 I_a 远大于磁绝缘最小电流 I_{amin})相比, 磁绝缘最小电流工作点时电子鞘层较厚, 鞘层电子流占总电流比例大, 电流非均匀分布的影响最显著. 另一方面, 用于闪光灯照相的MIVA装置次级MITL也大多运行在磁绝缘最小电流工作点^[38-40]. 因此, 本文讨论均针对MIVA次级磁绝缘运行在最小电流工作点. 需要强调的是, 磁绝缘最小电流工作点和自限制流工作点并不完全相同, 但两者差别极小, 工程上通常忽略两者之间的差异^[40].

2 非轴对称磁绝缘二维Creedon模型

MIVA次级非轴对称磁绝缘示意图如图1所示. 假定功率流沿轴向(z 方向)传输, 在垂直功率传输方向的二维(r, θ)平面上, 电流角向非均匀分布引起MITL阴-阳电极间隙电磁场非轴对称分布, 进而导致阴极表面电子非均匀发射. 当达到磁绝缘稳态时, 电子鞘层偏心.

假定磁绝缘稳态时满足以下条件^[36]: (1) 不考虑磁绝缘线阳极离子发射, 仅考虑阴极电子发射, 且满足

图1 (网络版彩图)圆柱坐标系下二维(r, θ)平面非轴对称磁绝缘示意图

Figure 1 (Color online) Sketch of the nonaxisymmetrical magnetic insulation of two-dimensional (r, θ) plane under the cylindrical coordinate.

空间电荷限制条件, 即稳态时阴极表面电场为零; (2) 与电磁场压强(电场和磁场能量密度)相比, 电子压强可忽略, 即阴极发射电子的初始能量和初始速度为零; (3) 磁绝缘稳态时, 空间电子沿 z 方向作等势位漂流.

基于以上模型假设条件, 推导磁绝缘电子在电子鞘层区域($r_c < r < r_s(\theta)$)和真空区域($r_s(\theta) < r < r_a$)内相对论因子 $\gamma_i(r, \theta)$ 和 $\gamma_o(r, \theta)$ 分别表示为^[30,36,41-43]

$$\gamma_i(r, \theta) = \cosh \left[a_0 \ln \left(\frac{r}{r_c} \right) + \sum_{j=0}^n a_j \cdot \left(\left(\frac{r}{r_c} \right)^j - \left(\frac{r_c}{r} \right)^j \right) \cdot \cos(j\theta) \right], \quad (1a)$$

$$\gamma_o(r, \theta) = \gamma_0 + b_0 \ln \left(\frac{r}{r_a} \right) + \sum_{j=0}^n b_j \cdot \left(\left(\frac{r}{r_a} \right)^j - \left(\frac{r_a}{r} \right)^j \right) \cdot \cos(j\theta), \quad (1b)$$

其中 n 为非负整数, 表征电流角向非均匀分布的模数. 系数 a_j, b_j ($0 \leq j \leq n, j$ 为整数)为待定常数, 其取值与边界条件(阴、阳极电流角向分布)密切相关, γ_0 为阳极相对论因子^[41-43].

当给定MITL运行参数(线电压 V_0 , 阴阳极半径 r_a, r_c)和阴极电流(或磁感应强度)角向分布时, 数值求解方程(1)可确定 $\gamma_i(r, \theta), \gamma_o(r, \theta)$ 和 $r_s(\theta)$ ^[43]. 在此基础上可获得磁绝缘电参数(电磁场、空间电子密度等)在二维(r, θ)平面上的分布.

MIVA感应腔电磁计算和注入电流空间分布实验均表明, 对于文献^[36]中感应腔及其角向线结构, 阴极磁感应强度的角向分量 $B_\theta(r_c, \theta)$ 在空间上满足余弦分

布. 假定 $B_\theta(r_c, \theta)$ 满足

$$B_\theta(r_c, \theta) = B_{c0} + B_{c0} \cdot \delta_c \cdot \cos(\theta), \quad (2)$$

其中 B_{c0} 为电流均匀分布的一维情况下阴极表面 B_θ . δ_c 用于表征二维情况下 $B_\theta(r_c, \theta)$ 角向非均匀分布的程度, 定义为阴极电流(或磁感应强度)不均匀系数.

需要强调的是, 前述物理模型虽然针对垂直功率流传输方向的二维 (r, θ) 截面, 但对于沿 z 方向磁绝缘特性发生变化的情形, 本模型依然适用, 此时可沿 z 方向离散出多个二维截面, 在每个截面上使用二维模型, 但需注意的是每个截面上模型求解输入条件(包括磁绝缘运行参数和 $B_\theta(r_c, \theta)$ 空间分布)不同.

3 电流非均匀分布对MIVA次级磁绝缘的影响

给定MITL工作参数: 线电压 $V_0=4.1$ MV (相对论因子 $\gamma_0=9$), $r_a=0.2$ m, $r_c=0.1$ m, MITL运行在磁绝缘最小电流工作点. 根据磁绝缘最小电流理论^[41,42], 当电流均匀分布时($\delta_c=0$), 计算得到阳极电流 $I_a=I_{amin}=132$ kA, 阴极电流 $I_{cmin}=65.5$ kA. 由安培环路定律得到 $B_{c0}=0.13$ T. 以下将改变阴极电流不均匀系数 δ_c , 以研究电流非均匀分布对磁绝缘电子鞘层和流阻抗的影响规律.

3.1 对磁绝缘电子鞘层的影响

在磁绝缘电子鞘层区域($r_c < r < r_s(\theta)$), 空间电子密度 $n_e(r, \theta)$ 可表示为^[36]

$$n_e(r, \theta) = \frac{\rho}{e} = \varepsilon \frac{\nabla \cdot E}{e} = -\frac{\varepsilon m_e c^2}{e^2} \nabla^2 \gamma_i. \quad (3)$$

采用文献^[43]中非轴对称磁绝缘电子鞘层的计算方法, 确定电子鞘层边界 $r_s(\theta)$ 和电子密度 $n_e(r, \theta)$. 图2给出了阴极电流不均匀系数 δ_c 取不同数值时 $n_e(r, \theta)$ 二维分布. 在 $\theta=0$ 角向位置, 由于磁感应强度 B_θ 较大, 电子受到的箍缩作用力较大, 因而电子鞘层较薄, 电子密度较大. 注入电流分布不均匀程度越大, 磁绝缘空间电子分布越不均匀, 电子鞘层偏心越严重. 当 δ_c 增大至69.5%时, 偏心的电子鞘层已扩散至阳极, 导致阴-阳间隙局部短路, 如图2(d)所示.

定义电子鞘层厚度 $d_s(\theta)$ 不均匀系数 ζ 为

$$\zeta = \frac{1}{2} \frac{\max(d_s(\theta)) - \min(d_s(\theta))}{\text{mean}(d_s(\theta))} \times 100\%, \quad (4)$$

$$d_s(\theta) = r_s(\theta) - r_c, \quad (5)$$

其中, $\max(d_s(\theta))$, $\min(d_s(\theta))$ 和 $\text{mean}(d_s(\theta))$ 分别为鞘层厚度 $d_s(\theta)$ 的最大值、最小值和平均值.

图3给出了电子鞘层厚度不均匀系数 ζ 随阴极电流不均匀系数 δ_c 的变化规律. ζ 随 δ_c 线性增大, 其数值约为 δ_c 的两倍, 这表明电子鞘层对阴极电流不均匀系数极为敏感.

3.2 对MITL流阻抗的影响

流阻抗 Z_f (Flow Impedance)在MITL电磁性能表征和电路模拟中具有重要应用, 其物理含义是电子鞘层电荷质心与阳极形成传输线的特征阻抗^[44-46]. 根据其物理定义, MITL磁绝缘流阻抗 Z_f 可表示为

$$Z_f = 60 \ln \left(\frac{r_a}{r_{eq}} \right). \quad (6)$$

磁绝缘电子的电荷质心位置 r_{eq} 为

$$r_{eq} = r_a - \frac{\int_{r_c}^{r_a} Q(r) \cdot dr}{Q_a}, \quad (7)$$

其中 $Q(r)$ 为内外半径分别为 r 和 r_c 的单位长度圆柱筒内电荷量. 在电流非均匀分布的二维情况下, 由高斯定律推导, $Q(r)$ 可表示为^[36,47]

$$Q(r) = \varepsilon r \int_0^{2\pi} E_r(r, \theta) d\theta. \quad (8)$$

图4给出了阴极电流不均匀系数 $\delta_c=25\%$ 时电荷量 $Q(r)$ 分布. 当 $\delta_c=35\%$ 时, 虽然电子鞘层发生显著偏心, 但在鞘层较厚的角向位置, 电子密度稀薄, 因而电荷质心位置并未发生显著变化. 与电流均匀分布($\delta_c=0$)时相比, 电荷质心位置由110.3 mm增大至114.0 mm, 流阻抗 Z_f 由35.8 Ω 降低至33.8 Ω (减小约5.6%). 图5给出了流阻抗变化与不均匀系数 δ_c 的关系. 与电子鞘层随不均匀系数 δ_c 急剧变化不同, 电荷质心位置 r_{eq} 和流阻抗 Z_f 对 δ_c 变化不敏感. 即使在偏心电子鞘层扩展至阳极(阴-阳间隙局部短路)的极端情况下($\delta_c=69.5\%$), 流阻抗 Z_f 约减小13%.

综上所述, 磁绝缘线阴极电流角向非均匀分布在一定程度上改变了MITL工作点, 引起流阻抗降低, 阴极发射更多电子, 阳极电流和磁绝缘鞘层电子流增大.

图2 (网络版彩图)不同 δ_c 时MITL间隙电子密度 $n_e(r, \theta)$ 二维分布. (a)–(d)角向不均匀系数 δ_c 分别为0.5%, 10%, 30%和69.5%. 磁绝缘线电压 $V_0=4.1$ MV ($\gamma_0=9$)、阳极电流 $I_a=I_{amin}=132$ kA

Figure 2 (Color online) 2D distributions of electron density under several different asymmetric coefficients of δ_c . The δ_c from (a) to (d) is 0.5%, 10%, 30%, and 69.5%, respectively. The calculations are under the following MITL parameters: $V_0=4.1$ MV, i.e., $\gamma_0=9$, and $I_a=I_{amin}=132$ kA.

图3 (网络版彩图)鞘层厚度不均匀系数 ζ 与阴极电流不均匀系数 δ_c 的关系

Figure 3 (Color online) Asymmetric coefficients of the electron sheath thickness, ζ , vary with the asymmetric coefficients of cathode current, δ_c .

需要强调的是, 阴-阳间隙局部短路时虽然流阻抗 Z_L 变化不显著, 但会引起感应腔输出叠加高频振荡, 从而降低MIVA装置辐射输出性能^[34]. 因此, 工程上应优化阴极电流空间分布, 避免这种极端情形发生^[28,29,36].

图4 (网络版彩图)电荷量分布 $Q(r)$ 和电荷质心位置($\delta_c=25\%$)

Figure 4 (Color online) Radial distribution of charge, $Q(r)$, also shown is the location of the charge centroid ($\delta_c=25\%$).

4 电流非均匀影响程度与磁绝缘参数的关系

电流非均匀分布的影响程度与MITL运行参数密切相关. 线电压 V_0 和最小阳极电流 I_{amin} 是描述MITL工

图5 (网络版彩图)流阻抗随阴极电流不均匀系数 δ_c 的变化规律

Figure 5 (Color online) Flow impedances vary with the asymmetric coefficients of cathode currents, δ_c .

作点最重要的两个参数^[40,46]. 当给定线电压 V_0 和最小电流 I_{amin} 时, 可确定MITL运行阻抗和真空阻抗^[38,39]. 对于 N 级感应腔串联MIVA装置, 次级MITL通常由 N 段组成, 中心内筒(阴极)尺寸逐渐减小^[38-40]. 理想情况下, 各级感应腔对应次级MITL阳极电流相同, 线电压和运行阻抗线性增大^[38-40]. 磁绝缘运行参数不同, 导致电流非均匀分布的影响程度不同.

4.1 磁绝缘线电压 V_0

以3级感应腔串联MIVA装置为例, 假定其输出电参数为4.2 MV/132 kA, 次级MITL阴极由3段外径尺寸

阶梯状减小的内筒组成, 1-3#级感应腔对应次级MITL的运行阻抗分别为10.6, 21.2和31.8 Ω . 理想情况下, 1-3# MITL最小阳极电流 I_{amin} 均为132 kA, 线电压分别为1.4, 2.8和4.2 MV. 图6给出了3级MIVA次级不同轴向位置处(每级感应腔出口)磁绝缘电子鞘层的二维分布. 处于MIVA上游的1#MITL电子鞘层偏心程度最大, 且由于1#MITL运行阻抗低、阴-阳极间隙距离短, 因此更容易出现电子鞘层偏心引发间隙局部短路的极端情况. 因此, 在最小阳极电流相同时, 线电压越低, 电流非均匀分布的影响程度越严重, MITL对阴极电流非均匀分布的容忍程度越低. 对于下游3# MITL (4.2 MV/132 kA), 当阴极电流不均匀系数为69.5%时, 电子鞘层偏心引起间隙局部短路, 但对于上游1# MITL (1.4 MV/132 kA), 当 δ 为35%时就发生间隙短路.

4.2 最小磁绝缘电流 I_{amin}

在MITL线电压相同时, 磁绝缘最小电流对电子鞘层的影响如图7所示. 图7给出了 $V_0=1.4$ MV, 最小电流 I_{amin} 分别为100, 132, 150和200 kA时的电子鞘层分布. I_{amin} 越小, 磁场强度越弱, 磁绝缘电子受到的箍缩作用力越小, 因此电流非均匀分布引起的电子鞘层偏心程度越严重. 然而当 I_{amin} 较小时, MITL运行阻抗较大, 阴-阳电极间距较大, 因此, 电子鞘层偏心引发间隙局部短路的极端情况不一定出现在 I_{amin} 较小时.

图6 (网络版彩图) 3级MIVA装置(4.2 MV/132 kA)次级不同轴向位置磁绝缘空间电子密度二维分布($\delta_c=25\%$). (a)-(c)分别为第1, 2和3级感应腔出口次级MITL电子鞘层分布, 其线电压分别为1.4, 2.8和4.2 MV, 最小磁绝缘阳极电流均为132 kA

Figure 6 (Color online) The 2D distributions of densities of magnetically-insulated electrons located at three different axial positions for a three-stage MIVA with electrical output of 4.2 MV and 132 kA. The positions are chosen to be the downstream of each cavity. The line-voltage for (a) to (c) is 1.4, 2.8, and 4.2 MV, respectively.

图7 (网络版彩图)磁绝缘最小电流 I_{amin} 对电子鞘层分布的影响. (a)–(d) I_{amin} 分别为100, 132, 150和200 kA, 线电压均为1.4 MV
Figure 7 (Color online) Influences of the minimum current of magnetic insulation, I_{amin} , on the distributions of electron sheath. The I_{amin} for (a) to (d) is 100, 132, 150, and 200 kA, respectively. And all the line-voltage is 1.4 MV.

5 结论

基于磁绝缘稳态二维Creedon物理模型, 理论推导了电子相对论因子在电子鞘层内、外区域满足的解析表达式. 当给定边界条件(磁绝缘线电压、阴极电流或磁感应强度角向分布)时, 数值求解获得了电子鞘层的二维分布. 结果表明, (1) 阴极电流分布对磁绝缘电子鞘层的影响程度较大, 电流非均匀分布造成电子鞘层偏心, 但并未引起磁绝缘

流阻抗(或工作点)发生显著改变. (2) 对于给定MITL运行参数($V_0=4.1$ MV, $I_a=I_{amin}=132$ kA), 电子鞘层厚度不均匀系数 ζ 约为阴极电流不均匀系数 δ_c 的两倍, 当 δ_c 增大至69.5%时, 偏心的电子鞘层扩展至阳极边界(局部短路), 此时流阻抗降低约13%. (3) 电流非均匀分布的影响程度与MITL运行参数密切相关, 在最小电流 I_{amin} 相同时, 线电压 V_0 越低, 电流非均匀分布的影响程度越严重. 对于多级串联MIVA装置, 上游MITL线电压较低, 因此对电流不均匀程度的容忍程度降低.

致谢 感谢西北核技术研究所“剑光一号”加速器团队给予的诸多帮助和有益建议.

参考文献

- 1 Mehlhorn T A. National security research in plasma physics and pulsed power: Past, present, and future. *IEEE Trans Plasm Sci*, 2014, 42: 1088–1117
- 2 Smith I, Corcoran P, Miller A R, et al. Pulse power for future and past X-ray simulators. *IEEE Trans Plasm Sci*, 2002, 30: 1746–1754
- 3 Goldsack T J, Bryant T F, Beech P F, et al. Multimegavolt multiaxis high-resolution flash X-ray source development for a new hydrodynamics research facility at AWE Aldermaston. *IEEE Trans Plasm Sci*, 2002, 30: 239–253

- 4 Bailey J E, Chandler G A, Cohen D, et al. Radiation science using Z-pinch X rays. *Phys Plasmas*, 2002, 9: 2186–2194
- 5 Stygar W A, Reisman D B, Stoltzfus B S, et al. Conceptual design of a 10^{13} W pulsed-power accelerator for megajoule-class dynamic-material-physics experiments. *Phys Rev Accel Beams*, 2016, 19: 070401
- 6 Stygar W A, Awe T J, Bailey J E, et al. Conceptual designs of two petawatt-class pulsed-power accelerators for high-energy-density-physics experiments. *Phys Rev ST Accel Beams*, 2015, 18: 110401
- 7 Reisman D B, Stoltzfus B S, Stygar W A, et al. Pulsed power accelerator for material physics experiments. *Phys Rev ST Accel Beams*, 2015, 18: 090401
- 8 Waisman E M, Reisman D B, Stoltzfus B S, et al. Optimization of current waveform tailoring for magnetically driven isentropic compression experiments. *Rev Sci Instrum*, 2016, 87: 063906
- 9 Greenly J B, Douglas J D, Hammer D A, et al. A 1 MA, variable risetime pulse generator for high energy density plasma research. *Rev Sci Instrum*, 2008, 79: 073501
- 10 Slutz S A, Stygar W A, Gomez M R, et al. Scaling magnetized liner inertial fusion on Z and future pulsed-power accelerators. *Phys Plasmas*, 2016, 23: 022702
- 11 Gomez M R, Slutz S A, Sefkow A B, et al. Experimental demonstration of fusion-relevant conditions in magnetized liner inertial fusion. *Phys Rev Lett*, 2014, 113: 155003
- 12 Stygar W A, Cuneo M E, Vesey R A, et al. Theoretical z-pinch scaling relations for thermonuclear-fusion experiments. *Phys Rev E*, 2005, 72: 026404
- 13 Wessel F J, Ur-Rahman H, Ney P, et al. Fusion in a staged Z-pinch. *IEEE Trans Plasm Sci*, 2015, 43: 2463–2468
- 14 Peng X J, Wang Z. Conceptual research on Z-pinch driven fusion-fission hybrid reactor (in Chinese). *High Power Laser Part Beams*, 2014, 26: 090201 [彭先觉, 王真. Z箍缩驱动聚变-裂变混合能源堆总体概念研究. *强激光与粒子束*, 2014, 26: 090201]
- 15 Deng J J, Wang M, Xie W P, et al. Super-power repetitive Z-pinch driver for fusion-fission reactor (in Chinese). *High Power Laser Part Beams*, 2014, 26: 100201 [邓建军, 王勐, 谢卫平, 等. 面向Z箍缩驱动聚变能源需求的超高功率重复频率驱动器技术. *强激光与粒子束*, 2014, 26: 100201]
- 16 Jones B, Coverdale C A, Deeney C, et al. Implosion dynamics and K-shell X-ray generation in large diameter stainless steel wire array Z pinches with various nesting configurations. *Phys Plasmas*, 2008, 15: 122703
- 17 Stygar W A, Ives H C, Fehl D L, et al. X-ray emission from z pinches at 10^7 A: Current scaling, gap closure, and shot-to-shot fluctuations. *Phys Rev E*, 2004, 69: 046403
- 18 Bennett G R, Vesey R A, Cuneo M E, et al. Symmetric inertial confinement fusion capsule implosions in a high-yield-scale double-Z-pinch-driven hohlraum on Z. *Phys Plasmas*, 2003, 10: 3717–3727
- 19 Sanford T W L, Olson R E, Mock R C, et al. Dynamics of a Z-pinch X-ray source for heating inertial-confinement-fusion relevant hohlraums to 120–160 eV. *Phys Plasmas*, 2000, 7: 4669–4682
- 20 Smith I D. Induction voltage adders and the induction accelerator family. *Phys Rev ST Accel Beams*, 2004, 7: 064801
- 21 Smith I, Corcoran P, Carboni V, et al. Induction voltage adder architectures and electrical characteristics. In: *Proceedings of the 14th IEEE International Pulsed Power Conference*, Piscataway, 2003. 371–378
- 22 Ramirez J J, Prestwich K R, Smith I D. High-power, short-pulse generators based on induction voltage adders. *Proc IEEE*, 1992, 80: 946–957
- 23 Ramirez J J, Prestwich K R, Johnson D L, et al. Performance of the Hermes-III gamma ray simulator. In: *Proceedings of the 7th IEEE International Pulsed Power Conference*, Piscataway, 1989. 26–31
- 24 Maenchen J, Cooperstein G, O'Malley J, et al. Advances in pulsed power-driven radiography systems. *Proc IEEE*, 2004, 92: 1021–1042
- 25 Sun F J, Qiu A C, Yang H L, et al. Pulsed X-ray source based on inductive voltage adder and rod pinch diode for radiography (in Chinese). *High Power Laser Part Beams*, 2010, 22: 936–940, [孙凤举, 邱爱慈, 杨海亮, 等. 感应电压叠加器驱动阳极杆箍缩二极管型脉冲X射线源. *强激光与粒子束*, 2010, 22: 936–940].
- 26 Comisso R J, Allen R J, Boller J R, et al. Status of the Mercury pulsed power generator, a 6-MV, 360-kA, magnetically-insulated inductive voltage adder. In: *Proceedings of the 14th IEEE International Pulsed Power Conference*, Piscataway, 2003. 383–386
- 27 Thomas K, Beech P, Brown S, et al. Status of the AWE hydruS IVA fabrication. In: *Proceedings of the 18th IEEE International Pulsed Power Conference*, Piscataway, 2011. 1042–1046
- 28 Smith I D, Bailey V L, Fockler J, et al. Design of a radiographic integrated test stand (RITS) based on a voltage adder, to drive a diode immersed in a high magnetic field. *IEEE Trans Plasm Sci*, 2000, 28: 1653–1659
- 29 Johnson D L, Smith I D, Corcoran P, et al. Magnetic insulation, power flow and pulse power results on RITS-3. In: *Proceedings of the 14th IEEE International High Power Beams Conference*, Piscataway, 2002. 123–126

- 30 Oliver B V, Genoni T C, Johnson D L, et al. Two and three-dimensional MITL power flow studies on RITS. In: Proceedings of the 14th IEEE International Pulsed Power Conference, Piscataway, 2003. 395–398
- 31 Wei H, Sun F, Yin J, et al. Current density distributions on the cathode plates of inductive voltage cells. *IEEE Trans Plasm Sci*, 2014, 42: 2846–2847
- 32 Bruner N, Mostrom C, Rose D V, et al. Modeling the RITS-6 transmission line. In: Proceedings of the 16th IEEE International Pulsed Power Conference, Piscataway, 2007. 807–810
- 33 Bruner N, Genoni T, Madrid E, et al. Modeling particle emission and power flow in pulsed-power driven, nonuniform transmission lines. *Phys Rev ST Accel Beams*, 2008, 11: 040401
- 34 Bruner N, Genoni T, Madrid E, et al. Excitation of voltage oscillations in an induction voltage adder. *Phys Rev ST Accel Beams*, 2009, 12: 070401
- 35 Wei H, Sun F, Liang T, et al. Low voltage pulse injection test of a single-stage 1 MV prototype induction voltage adder cell. *Rev Sci Instrum*, 2014, 85: 083506
- 36 Wei H. The Characteristics of Spatial Distributions of Injection Currents and their Effects on the Secondary Magnetic Insulation in Induction Voltage Adders (in Chinese). Dissertation for Doctoral Degree. Xi'an: Xi'an Jiaotong University, 2017 [魏浩. 感应电压叠加器注入电流空间分布及对次级磁绝缘的影响. 博士学位论文. 西安: 西安交通大学, 2017]
- 37 Qian B L, Li C L, Liu Y G, et al. Two-dimensional analysis of the relativistic parapotential electron flow in a magnetically insulated transmission line oscillator (MILO). *IEEE Trans Plasm Sci*, 2000, 28: 760–766
- 38 Pate R C, Patterson J C, Dowdican M C, et al. Self-magnetically insulated transmission line (MITL) system design for the 20-stage Hermes-III accelerator. In: Proceedings of the 6th IEEE International Pulsed Power Conference, Piscataway, 1987. 478–481
- 39 Allen R J, Commisso R J, Cooperstein G, et al. Extension of the operating point of the Mercury IVA from 6 to 8 MV. In: Proceedings of the 18th IEEE International Pulsed Power Conference, Piscataway, 2011. 1036–1041
- 40 Ottinger P F, Schumer J W. Rescaling of equilibrium magnetically insulated flow theory based on results from particle-in-cell simulations. *Phys Plasmas*, 2006, 13: 063109
- 41 Creedon J M. Magnetic cutoff in high-current diodes. *J Appl Phys*, 1977, 48: 1070–1077
- 42 Creedon J M. Relativistic Brillouin flow in the high v/γ diode. *J Appl Phys*, 1975, 46: 2946–2955
- 43 Wei H, Sun F J, Hu Y X, et al. A method to calculate the electron sheath profile of the nonaxisymmetrical magnetic insulation (in Chinese). *Acta Phys Sin*, 2017, 66: 038402 [魏浩, 孙凤举, 呼义翔, 等. 一种非轴对称磁绝缘电子鞘层边界的计算方法. 物理学报, 2017, 66: 038402]
- 44 Mendel C W Jr., Rosenthal S E. Modeling magnetically insulated devices using flow impedance. *Phys Plasmas*, 1995, 2: 1332–1342
- 45 Mendel C W Jr., Seidel D B. Flow impedance in a uniform magnetically insulated transmission line. *Phys Plasmas*, 1999, 6: 4791–4793
- 46 Ottinger P F, Schumer J W, Hinshelwood D D, et al. Generalized model for magnetically insulated transmission line flow. *IEEE Trans Plasma Sci*, 2008, 36: 2708–2721
- 47 Ma X K. Theory and Application of Electromagnetic Field (in Chinese). Xi'an: Xi'an Jiaotong University Press, 2000 [马西奎. 电磁场理论及应用. 西安: 西安交通大学出版社, 2000]

Effects of current asymmetry on the electron sheath of magnetically-insulated induction voltage adders

WEI Hao^{1,2*}, SUN FengJu², QIU AiCi^{1,2} & HU YiXiang²

¹State Key Laboratory of Electrical Insulation and Power Equipment, Xi'an Jiaotong University, Xi'an 710049, China;

²State Key Laboratory of Intense Pulsed Radiation Simulation and Effect, Northwest Institute of Nuclear Technology, Xi'an 710024, China

The current asymmetry resulting from the special injection manner of cavities in magnetically-insulated induction voltage adders (MIVA) would affect the electron sheath and power flow of the magnetically-insulated transmission lines (MITL). In this article, based on the two-dimensional Creedon equilibrium flow of the magnetic insulation, the effects of current asymmetry on the electron sheath are evaluated. It is found that, the current asymmetry affects the electron sheath more greatly than the charge centroid and flow impedance. For the given parameters of MITL (e.g., the line voltage V_0 is 4.1 MV, and the minimal anode current I_{amin} is 132 kA), the asymmetric coefficient of the electron sheath is about 79.4% when the asymmetric coefficient of cathode currents, δ_c , is 35%. And the flow impedance decreases by 5.6% compared with the case of no current asymmetry. As the δ_c increases to 69.5%, the AK gap is short circuit at some positions due to the off-center electron sheath. It is also found that, the lower of the line voltage V_0 and the minimal anode current I_{amin} are, the larger of the influence extent of current asymmetry is. As the line voltage decreases from the 4.2 to 1.4 MV, the critical value of asymmetric coefficients of cathode currents leading to the gap closure, decreases from 69.5% to 35%.

magnetically-insulated induction voltage adders (MIVA), current asymmetry, nonaxisymmetrical magnetic insulation, electron sheath

PACS: 52.59.-f, 29.20.Ej, 41.75.Ht, 41.20.Cv, 84.70.+p

doi: [10.1360/SSPMA2017-00263](https://doi.org/10.1360/SSPMA2017-00263)